

SK-0330-M

Fixed Plate LCD Digital Orbital Shaker



SK-0180-S LED Digital Orbital Shaker



Features

- · Double-screen display for time and speed respectively
- Compact footprint
- · Provides smooth and uniform shaking
- Two options:
 9.8kg (O330-M) and speed range 70-400rpm,
 3.1kg (O180-S) and speed range 40-200rpm
- · Continuous or timer operation mode
- · Maintenance- free brushless DC motor
- · Over speed detection and protection

Applications

Orbital Shaker is ideal for applications like bacterial suspension, solubility studies, growth of bacteria and yeast, extraction procedures, washing procedures, diagnostics tests, hybridization, general mixing, staining & destaining, mixing, and extracting.

It is suitable for almost any vessel from micro-centrifuge tubes through petri dishes and microplates to conical flasks.









Multifunctional models (multiple plate are optional)

Specifications	SK-0180-S	SK-0330-M
Orbital diameter	20mm	10mm
ax. load capacity (with platform)	2kg	3kg
Motor type	Brushless DC motor	Brushless DC motor
Motor input power	20W	20W
Motor output power	16W	15W
Speed range	40-200rpm	70-400rpm
Speed display	LED	LCD
Timer display	LED	LCD
Time settings range	1min-99h59min	1min-99h59min
Voltage,Frequency	100-240V,50/60Hz	100-240V,50/60Hz
Power	20W	25W
Weight	3.1kg	9.8kg
Permissible ambient temperature and humidity	5-40°C,80%RH	5-40°C,80%RH
$Dimension[W \times D \times H]$	294×348×123mm	420×370×100mm
Protection class	IP21	IP21
Work plate Dimension [W x D]	268x268mm	335×335mm



Pricing on any accessories shown can be found by keying the part number into the search box on our website.

The specifications listed in this brochure are subject to change by the manufacturer and therefore cannot be guaranteed to be correct. If there are aspects of the specification that must be guaranteed, please provide these to our sales team so that details can be confirmed.

www.wolflabs.co.uk

Tel: 01759 301142

Fax: 01759 301143

sales@wolflabs.co.uk

Please contact us if this literature doesn't answer all your questions.